

Auto Voltage Stabilizer (1 Ph. Relay type)

POWER HOUSE™



**Guard
Your Appliances/
Equipments against erratic
Voltage Fluctuations**

**HEAVY DUTY
ROBUST
RELIABLE
COMS-ICS CONTROL**

- Input Range : 50-280 V. 1 Phase (select from different Models)
- Out put range : 200-240 V.
- Indications: : LED for mains ON
- Instruments : Volt Meter with SS for input and out put (1000VA & above)
- : LED input range for 200 & 500 VA models.
- Transformer : Copper wound, Heavy duty.
- Control Circuit : CMOS IC based
- Housing : SS suitable for table top mounting
- Protection : Fuse (250 VA & 500 VA) / MCB for higher ratings.
- Delay Timer : For input voltage range of 50, 75 & 100- 280 V.
- : cab also be provided with other models at extra cost
- Over Load : Electronics Over Load cut out protection can be provided at extra cost.

Wide Range to Select from

Capacity VA	Model No.	Input Volts	Load A.
250	PSR-217	175-250	1.1
	PSR-215	150-270	
	PSR-213	130-250	
	PSR-210	100-290	
	PSR-205	75-270	
500	PSR-208	50-270	2.2
	PSR-516	160-265	
	PSR-513	130-280	
	PSR-510	100-280	
1000	PSR-507	75-270	4.4
	PSR-505	50-270	
	PSR-1017	175-280	
	PSR-1016	160-280	
	PSR-1013	130-280	
2000	PSR-1010	100-280	8.8
	PSR-1007	75-270	
	PSR-1005	50-270	
	PSR-2017	175-280	
	PSR-2016	160-280	
	PSR-2013	130-280	
3000	PSR-2010	100-280	13.2
	PSR-2007	75-270	
	PSR-2005	50-270	
	PSR-3017	175-280	
	PSR-3013	130-280	
4000	PSR-3010	100-280	17.6
	PSR-3007	75-270	
	PSR-3005	50-270	
	PSR-4017	175-280	
	PSR-4013	130-280	
5000	PSR-4010	100-280	22
	PSR-4007	75-275	
	PSR-4005	50-270	
	PSR-5017	175-280	
	PSR-5013	130-280	
7500	PSR-5009	90-280	33
	PSR-5007	75-270	
	PSR-5005	50-280	
	PSR-7517	175-280	
10000	PSR-7513	130-280	44
	PSR-7510	100-280	
	PSR-7507	75-275	
	PSR-10017	175-280	
	PSR-10013	130-280	
	PSR-10010	100-280	
	PSR-10009	90-270	



POWER SERVICES
Innovative Power Solutions

33, Phears Lane, Kolkata -700 073
Ph./Fax (033) 2237-0508, 2236-0575.
Email: info@indiapowerhouse.net
Visit us at www.indiapowerhouse.com